



CAUTION: For continued protection against risk of fire, replace only with same type of fuse having the same electrical rating!



QUICK REFERENCE FUSE CHART

Backbox Fuses

LOC: DISPLAY POWER SUPPLY (P.S.) BOARD

| | | | |
|-----------|----------------|--------|----------------------|
| F1 | 3/4A 250v S.B. | 90v DC | High Voltage Display |
|-----------|----------------|--------|----------------------|

LOC: I / O POWER DRIVER BOARD

| | | | |
|-----------|--------------|--------|-----------------------------------|
| F6 | 7A 250v S.B. | 50v DC | Primary High Power Coils/Flippers |
|-----------|--------------|--------|-----------------------------------|

| | | | |
|-----------|--------------|--------|-----------------|
| F7 | 5A 250v S.B. | 20v DC | Low Power Coils |
|-----------|--------------|--------|-----------------|

| | | | |
|-----------|--------------|--------|-------------|
| F8 | 5A 250v S.B. | 12v DC | Logic Power |
|-----------|--------------|--------|-------------|

| | | | |
|-----------|--------------|--------|-------------|
| F9 | 5A 250v S.B. | 12v DC | Logic Power |
|-----------|--------------|--------|-------------|

| | | | |
|------------|--------------|--------|------------------------------------|
| F20 | 3A 250v S.B. | 50v DC | Magnets/Aux. (If used, see Manual) |
|------------|--------------|--------|------------------------------------|

| | | | |
|------------|--------------|--------|-------|
| F21 | 3A 250v S.B. | 50v DC | Coils |
|------------|--------------|--------|-------|

| | | | |
|------------|--------------|--------|------------------|
| F22 | 8A 250v S.B. | 18v DC | Controlled Lamps |
|------------|--------------|--------|------------------|

| | | | |
|------------|--------------|-------|-------|
| F23 | 4A 250v S.B. | 5v DC | Logic |
|------------|--------------|-------|-------|

| | | | |
|------------|--------------|---------|---------------------------------|
| F24 | 5A 250v S.B. | 6.3v AC | G.I. Lamps (BRN-WHT to WHT-BRN) |
|------------|--------------|---------|---------------------------------|

| | | | |
|------------|--------------|---------|-----------------------------|
| F25 | 5A 250v S.B. | 6.3v AC | G.I. Lamps (YEL to WHT-YEL) |
|------------|--------------|---------|-----------------------------|

| | | | |
|------------|--------------|---------|-----------------------------|
| F26 | 5A 250v S.B. | 6.3v AC | G.I. Lamps (GRN to WHT-GRN) |
|------------|--------------|---------|-----------------------------|

| | | | |
|------------|--------------|---------|-----------------------------|
| F27 | 5A 250v S.B. | 6.3v AC | G.I. Lamps (VIO to WHT-VIO) |
|------------|--------------|---------|-----------------------------|

| | | | |
|------------|--------------|--------|-----------------------------------|
| F28 | 3A 250v S.B. | 24v AC | Motors/Aux. (If used, see Manual) |
|------------|--------------|--------|-----------------------------------|

Cabinet Fuses

LOC: SERVICE (AC) OUTLET BOX (Cabinet Bottom)

| | | | |
|------------|--------------|---------|----------------------------------|
| n/a | 8A 250v S.B. | 115v AC | Main Fuse Line (Domestic or USA) |
|------------|--------------|---------|----------------------------------|

| | | | |
|------------|--------------|---------|--------------------------------|
| n/a | 5A 250v S.B. | 220v AC | Main Fuse Line (International) |
|------------|--------------|---------|--------------------------------|

Playfield Fuses

LOC: UNDER PLAYFIELD (near Flippers)

| | | | |
|------------|--------------|--------|---------------------------------|
| n/a | 3A 250v S.B. | 50v DC | Rt. Flipper (BLU-YEL ↔ RED-YEL) |
|------------|--------------|--------|---------------------------------|

| | | | |
|------------|--------------|--------|---------------------------------|
| n/a | 3A 250v S.B. | 50v DC | Lt. Flipper (GRY-YEL ↔ RED-YEL) |
|------------|--------------|--------|---------------------------------|

| | | | |
|------------|--------------|--------|-------------------------------------|
| n/a | 3A 250v S.B. | 50v DC | Add'l Flipper (If used, see Manual) |
|------------|--------------|--------|-------------------------------------|