

Gottlieb's Volcano

Switch Matrix

	RETURN 0 A1J6-10 Blu-Blk-Blk (600)	RETURN 1 A1J6-11 Blu-Brn-Brn (611)	RETURN 2 A1J6-12 Blu-Red-Red (622)	RETURN 3 A1J6-13 Blu-Orn-Orn (633)	RETURN 4 A1J6-14 Blu-Yel-Yel (644)	RETURN 5 A1J6-15 Blu-Grn-Grn (655)	RETURN 6 A1J5-8 / A1J6-16 Blu-Blu-Blu (666)	RETURN 7 A1J5-1 / A1J6-17 Blu-Pur-Pur (677)
STROBE 0 A1J5-2 / A1J6-1 Yel-Blk-Blk (400)	#1 Subway Blk-Blk-Blk (000) SW.00	#1 Right Drop Target Pur-Blk-Blk (700) SW.01	#1 Top Drop Target Brn-Yel-Yel (144) SW.02	Not Used SW.03	Crater #4 Rollover Brn-Blk-Blk (100) SW.04	Right Outlane Rollover Orn-Pur-Pur (377) SW.05	Left Outlane Rollover Brn-Pur-Pur (177) SW.06	Test Button Grn-Blk-Blk (500) SW.07
STROBE 1 A1J5-4 / A1J6-2 Yel-Brn-Brn (411)	#2 Subway Blk-Slt-Slt (088) SW.10	#2 Right Drop Target Pur-Brn-Brn (711) SW.11	#2 Top Drop Target Grn-Grn-Grn (555) SW.12	Bottom Pop Bumpers (2) Orn-Yel-Yel (344) SW.13	Crater #3 Brn-Brn-Brn (111) SW.14	10 Point Switches (7) Slt-Yel-Yel (844) SW.15	Left Return Rollover Slt-Orn-Orn (833) SW.16	Left Coin Chute Grn-Brn-Brn (511) SW.17
STROBE 2 A1J5-4 / A1J6-3 Yel-Red-Red (422)	Outhole Blk-Pur-Pur (077) SW.20	#3 Right Drop Target Pur-Red-Red (722) SW.21	#3 Top Drop Target Grn-Blu-Blu (566) SW.22	Hole Kicker Slt-Brn-Brn (811) SW.23	Crater #2 Brn-Red-Red (122) SW.24	Rollunder Orn-Blu-Blu (366) SW.25	Kicking Target Slt-Blk-Blk (800) SW.26	Right Coin Chute Grn-Red-Red (522) SW.27
STROBE 3 A1J5-5 / A1J6-4 Yel-Orn-Orn (433)	Right Trough Brn-Grn-Grn (155) SW.30	#4 Right Drop Target Pur-Orn-Orn (733) SW.31	#4 Top Drop Target Grn-Pur-Pur (577) SW.32	Not Used SW.33	Crater #1 Brn-Orn-Orn (133) SW.34	Top Pop Bumpers (2) Orn-Grn-Grn (355) SW.35	Spot Target Slt-Grn-Grn (855) SW.36	Center Coin Chute Grn-Orn-Orn (533) SW.37
STROBE 4 A1J5-6 / A1J6-5 Yel-Yel-Yel (444)	Left Trough Brn-Blu-Blu (166) SW.40	#5 Right Drop Target Pur-Yel-Yel (744) SW.41	#5 Top Drop Target Grn-Slt-Slt (588) SW.42	Fire Pit Kicker Slt-Pur-Pur (877) SW.43	Spinner Pur-Blu-Blu (766) SW.44	Not Used SW.45	Tilt Grn-Grn-Grn (555) Blk-Yel-Yel (044) SW.46	Replay Button Grn-Yel-Yel (544) SW.47
STROBE 5 A1J5-7 / A1J6-6 Yel-Grn-Grn (455)	Not Used SW.50	Not Used SW.51	Not Used SW.52	Not Used SW.53	Not Used SW.54	Not Used SW.55	Shooter Guide Button Slt-Blu-Blu (866) SW.56	Not Used SW.57
STROBE 6 A1J6-7 Yel-Blu-Blu (466)	Not Used SW.60	Not Used SW.61	Not Used SW.62	Not Used SW.63	Not Used SW.64	Not Used SW.65	Not Used SW.66	Not Used SW.67
STROBE 7 A1J5-9 / A1J6-8 Yel-Pur-Pur (477)	Not Used SW.70	Not Used SW.71	Not Used SW.72	Not Used SW.73	Not Used SW.74	Not Used SW.75	Not Used SW.76	Not Used SW.77

Gottlieb's Volcano

Driverboard

transistor	connector	code	description	wire code	wire color	transistor type
Q01	A3J3-A	L0	Game Over Relay (Q)	288	Red-Slt-Slt	MPS-U45
Q Relay			Match	011	Blk-Brn-Brn	Q relay n.c.
Q Relay			Ball in Play	033	Blk-Orn-Orn	Q relay n.o.
Q02	A3J3-B	L1	Tilt Relay (T)	277	Red-Pur-Pur	MPS-U45
T Relay			Tilt	022	Brn-Red-Red	T relay n.o.
Q03	A3J5-2	L2	Coin Lockout	877	Slt-Pur-Pur	MPS-U45
Q04	A3J2-1 / A3J3-C	L3	Same Player Shoot Again	588	Grn-Slt-Slt	MPS-U45
Q05	A3J2-2	L4	Seismic Multiplier 2X	500	Grn-Blk-Blk	MPS-A13
Q06	A3J2-3	L5	Seismic Multiplier 3X	511	Grn-Brn-Brn	MPS-A13
Q07	A3J2-5	L6	Seismic Multiplier 4X	522	Grn-Red-Red	MPS-A13
Q08	A3J2-4	L7	Seismic Multiplier 5X	533	Grn-Orn-Orn	MPS-A13
Q09	A3J2-10	L8	Fire Pit	544	Grn-Yel-Yel	MPS-U45 + UPT
Q10	A3J2-9	L9	Not Used	555	Grn-Grn-Grn	MPS-A13
Q11	A3J2-7	L10	High Game To Date	577	Grn-Pur-Pur	MPS-A13
Q12	A3J2-8	L11	Game Over	566	Grn-Blu-Blu	MPS-A13
Q13	A3J3-25	L12	Motor Relay	100	Brn-Blk-Blk	MPS-U45
Q14	A3J3-24	L13	Ball Saver Relay	111	Brn-Brn-Brn	MPS-U45
Q15	A3J3-22	L14	Right Ball Gate	122	Brn-Red-Red	MPS-U45
Q16	A3J3-23	L15	Ball Release	133	Brn-Orn-Orn	MPS-U45 + UPT
Q17	A3J3-13	L16	Hole Kicker	144	Brn-Yel-Yel	MPS-U45 + UPT
Q18	A3J3-14	L17	Lava Level One	155	Brn-Grn-Grn	MPS-U45
Q19	A3J3-16	L18	Lava Level Two	166	Brn-Blu-Blu	MPS-U45
Q20	A3J3-15	L19	#1 Drop Target (2)	177	Brn-Pur-Pur	MPS-U45
Q21	A3J3-21	L20	#2 Drop Target (2)	300	Orn-Blk-Blk	MPS-U45
Q22	A3J3-20	L21	#3 Drop Target (2)	311	Orn-Brn-Brn	MPS-U45
Q23	A3J3-18	L22	#4 Drop Target (2)	322	Orn-Red-Red	MPS-U45
Q24	A3J3-19	L23	#5 Drop Target (2)	333	Orn-Orn-Orn	MPS-U45
Q25	A3J3-9	L24	Crater 4	344	Orn-Yel-Yel	MPS-U45
Q26	A3J3-10	L25	Crater 3	355	Orn-Grn-Grn	MPS-U45
Q27	A3J3-12	L26	Crater 2	366	Orn-Blu-Blu	MPS-U45
Q28	A3J3-11	L27	Crater 1	377	Orn-Pur-Pur	MPS-U45
Q29	A3J3-Y	L28	Top Drop Target	500	Grn-Blk-Blk	MPS-U45
Q30	A3J3-X	L29	Bottom Drop Target	511	Grn-Brn-Brn	MPS-U45
Q31	A3J3-V	L30	2X Lava Flow Multiplier	522	Grn-Red-Red	MPS-U45
Q32	A3J3-W	L31	3X Lava Flow Multiplier	533	Grn-Orn-Orn	MPS-U45
Q33	A3J3-5	L32	4X Lava Flow Multiplier	544	Grn-Yel-Yel	MPS-A13
Q34	A3J3-6	L33	1000 Bonus	555	Grn-Grn-Grn	MPS-A13
Q35	A3J3-K	L34	2000 Bonus	566	Grn-Blu-Blu	MPS-A13
Q36	A3J3-7	L35	3000 Bonus	577	Grn-Pur-Pur	MPS-A13
Q37	A3J4-1	L36	4000 Bonus	700	Pur-Blk-Blk	MPS-A13
Q38	A3J4-2	L37	5000 Bonus	711	Pur-Brn-Brn	MPS-A13
Q39	A3J4-4	L38	6000 Bonus	722	Pur-Red-Red	MPS-A13
Q40	A3J4-3	L39	7000 Bonus	733	Pur-Orn-Orn	MPS-A13
Q41	A3J3-4	L40	8000 Bonus	744	Grn-Yel-Yel	MPS-A13
Q42	A3J3-3	L41	9000 Bonus	755	Grn-Grn-Grn	MPS-A13
Q43	A3J3-T	L42	10,000 Bonus	766	Grn-Blu-Blu	MPS-A13
Q44	A3J3-2	L43	Spot Target	777	Grn-Pur-Pur	MPS-A13
Q45	A3J3-D	L44	Special	800	Slt-Blk-Blk	MPS-U45
Q46	A3J3-F	L45	Extra Ball	811	Slt-Brn-Brn	MPS-U45
Q47	A3J3-P	L46	Spinner	822	Slt-Red-Red	MPS-U45
Q48	A3J3-M	L47	Collect Seismic Value	833	Slt-Orn-Orn	MPS-U45
Q49	A3J3-E	L48	Not Used	844	Slt-Yel-Yel	MPS-U45
Q50	A3J3-H	L49	Not Used	855	Slt-Grn-Grn	MPS-U45
Q51	A3J3-R	L50	Not Used	866	Slt-Blu-Blu	MPS-U45
Q52	A3J3-N	L51	Not Used	877	Slt-Pur-Pur	MPS-U45
Q53	A3J5-8	Solenoid 8	Knocker	888	Slt-Slt-Slt	2N6043
Q54	A3J6-3	Solenoid 3	Coin Counter 1	655	Blu-Grn-Grn	MPS-U45
Q55	A3J6-2	Solenoid 4	Coin Counter 2	644	Blu-Yel-Yel	MPS-U45
Q56	A3J6-1	Solenoid 7	Coin Counter 3	633	Blu-Orn-Orn	MPS-U45
Q57-Q58	A3J4-13	Solenoid 2	Top Drop Target Bank Reset	200	Red-Blk-Blk	MPS-U45 - 2N3055
Q59	A3J4-8	Solenoid 9	Outhole	244	Red-Yel-Yel	2N6043
Q60	A3J4-7	Solenoid 1	Subway Ball Release	266	Red-Blu-Blu	2N6043
Q61-Q62	A3J4-6	Solenoid 5	Subway Kicker	211	Red-Brn-Brn	MPS-U45 - 2N3055
Q63-Q64	A3J4-12	Solenoid 6	Right Drop Target Bank Reset	233	Red-Orn-Orn	MPS-U45 - 2N3055

Gottlieb's Volcano

Fuse List

designation	Wire in	Value	Wire out	description	location
F1	Blk-Slt-Slt (088)	8 Amp Slo-Blo	Blk-Pur-Pur (077)	6.3VAC Lightbox Illumination	Bottom Board
F2		8 Amp Slo-Blo	Blk-Blu-Blu (066)	6.3VAC Playboard Illumination	Bottom Board
F3	Orn-Blk-Blk (300)	7½ Amp Slo-Blo	Orn-Brn-Brn (311)	8VAC Controlled Lamps	Bottom Board
F4	Orn-Red-Red (322)	2 Amp Slo-Blo	Orn-Orn-Orn (333)	12VAC Sound Board	Bottom Board
F5	Red-Brn-Brn (211)	5 Amp Slo-Blo	Red-Orn-Orn (233)	10VAC Power Supply	Bottom Board
F6	Red-Blu-Blu (266)	8 Amp Slo-Blo	Red-Pur-Pur (277)	25VAC Solenoids	Bottom Board
F7	Brn-Slt-Slt (188)	¼ Amp Slo-Blo	Brn-Blk-Blk (100)	60VAC Score Displays	Bottom Board
F8	--	5 Amp Slo-Blo	Grn-Slt-Slt (588)	115VAC Primary Fuse	Bottom Board
		2½ Amp Slo-Blo		230VAC Primary Fuse	Bottom Board
F9	Grn-Blu-Blu (566)	1 Amp Slo-Blo	Orn-Blu-Blu (366)	24VDC Sound / Speech Power Supply	Cabinet
F10	Orn-Slt-Slt (388)	2½ Amp Slo-Blo	Red-Blu-Blu (266)	Center Pop Bumper	Playfield
F11	Orn-Slt-Slt (388)	2½ Amp Slo-Blo	Red-Blk-Blk (200)	Left Top Pop Bumper	Playfield
F12	Orn-Slt-Slt (388)	2½ Amp Slo-Blo	Red-Orn-Orn (233)	Right Bottom Pop Bumper	Playfield
F13	Orn-Slt-Slt (388)	2½ Amp Slo-Blo	Red-Brn-Brn (211)	Left Bottom Pop Bumper	Playfield
F14	Red-Red-Red (222)	2 Amp Slo-Blo	Red-Grn-Grn (255)	Outhole	Playfield
				Subway Ball Release	
F15	Red-Red-Red (222)	2½ Amp Slo-Blo	Red-Yel-Yel (244)	Top Drop Target Bank Reset	Playfield
				Right Drop Target Bank Reset	
				Subway Kicker	
F16	Red-Red-Red (222)	2 Amp Slo-Blo	?	Fire Pit	Playfield
F17	Red-Red-Red (222)	2½ Amp Slo-Blo	?	Hole Kicker	Playfield
				Ball Release	

www.inkochnito.nl

Solenoids

	Solenoid description	Solenoid Type	Power Wire	Fuse	Transfer Wire	Coil Wire Color	Connector	Driver Tr.	Transistor Type	Coil Type
L0	Game Over Relay	controlled	Red-Red-Red (222)			Red-Slt-Slt (288)	A3J3-A	Q1	MPS-U45	A-16890
L1	Tilt Relay	controlled	Red-Red-Red (222)			Red-Pur-Pur (277)	A3J3-B	Q2	MPS-U45	A-16890
L2	Lockout	controlled	Red-Red-Red (222)			Slt-Pur-Pur (877)	A3J5-2	Q3	MPS-U45	A-16890
L8	Fire Pit	controlled	Red-Red-Red (222)	F16	?	Grn-Yel-Yel (544)	A3J2-10	Q9 + UTP	MPS-U45 - 2N5875	A-4893
L12	Motor Relay	controlled	Orn-Slt-Slt (388)			Brn-Blk-Blk (100)	A3J3-25	Q13	MPS-U45	A-16890
L13	Ball Saver Relay	controlled	Orn-Slt-Slt (388)			Brn-Brn-Brn (111)	A3J3-24	Q14	MPS-U45	A-16890
L14	Right Ball Gate	controlled	Orn-Slt-Slt (388)			Brn-Red-Red (122)	A3J3-22	Q15	MPS-U45	A-20558
L15	Ball Release	controlled	Red-Red-Red (222)	F17	?	Brn-Orn-Orn (133)	A3J3-23	Q16 + UTP	MPS-U45 - 2N5875	A-16570
L16	Hole Kicker	controlled	Red-Red-Red (222)	F17	?	Brn-Yel-Yel (144)	A3J3-13	Q17 + UTP	MPS-U45 - 2N5875	A-5195
Sol. 1	Subway Ball Release	controlled	Red-Red-Red (222)	F14	Red-Grn-Grn (255)	Red-Blu-Blu (266)	A3J4-7	Q60	2N6043	A-16570
Sol. 2	Top Drop Target Bank Reset	controlled	Red-Red-Red (222)	F15	Red-Yel-Yel (244)	Red-Blk-Blk (200)	A3J4-13	Q57 + Q58	MPS-U45 + 2N3055	A-17891
Sol. 3	Coin Counter #1	controlled	Red-Red-Red (222)			Blu-Grn-Grn (655)	A3J6-3	Q54	MPS-U45	
Sol. 4	Coin Counter #2	controlled	Red-Red-Red (222)			Blu-Yel-Yel (644)	A3J6-2	Q55	MPS-U45	
Sol. 5	Subway Kicker	controlled	Red-Red-Red (222)	F15	Red-Yel-Yel (244)	Red-Brn-Brn (211)	A3J4-6	Q61 + Q62	MPS-U45 + 2N3055	A-4893
Sol. 6	Right Drop Target Bank Reset	controlled	Red-Red-Red (222)	F15	Red-Yel-Yel (244)	Red-Orn-Orn (233)	A3J4-12	Q63 + Q64	MPS-U45 + 2N3055	A-17891
Sol. 7	Coin Counter #3	controlled	Red-Red-Red (222)			Blu-Orn-Orn (633)	A3J6-1	Q56	MPS-U45	
Sol. 8	Knocker	controlled	Red-Red-Red (222)			Slt-Slt-Slt (888)	A3J5-8	Q53	2N6043	A-5195
Sol. 9	Outhole	controlled	Red-Red-Red (222)	F14	Red-Grn-Grn (255)	Red-Yel-Yel (244)	A3J4-8	Q59	2N6043	A-16570
	Left Bottom Pop Bumper	Pop Bumper Board	Orn-Slt-Slt (388)	F13	Red-Brn-Brn (211)	Brn-Slt-Slt (188)	1A8J1-1	board 1 - Q1	2N6057	A-1496
	Right Bottom Pop Bumper	Pop Bumper Board	Orn-Slt-Slt (388)	F12	Red-Orn-Orn (233)	Yel-Slt-Slt (488)	2A8J1-1	board 2 - Q1	2N6057	A-1496
	Left Top Pop Bumper	Pop Bumper Board	Orn-Slt-Slt (388)	F11	Red-Blk-Blk (200)	Slt-Slt-Slt (888)	3A8J1-1	board 3 - Q1	2N6057	A-1496
	Center Pop Bumper	Pop Bumper Board	Orn-Slt-Slt (388)	F10	Red-Blu-Blu (266)	Red-Pur-Pur (277)	4A8J1-1	board 4 - Q1	2N6057	A-1496
	Ball Saver Coil	left cabinet button	Red-Red-Red (222)	to button,	Blk-Orn-Orn (033)	Red-Orn-Orn (233)	to coil	switch		A-4893
	Top Left Kicking Rubber	directly	Orn-Slt-Slt (388)					switch		A-1496
	Lower Left Kicking Rubber	directly	Orn-Slt-Slt (388)					switch		A-1496
	Right Kicking Rubber	directly	Orn-Slt-Slt (388)					switch		A-1496
	Kicking Target	directly	Orn-Slt-Slt (388)					switch		A-5194
	Left Flipper	directly	Orn-Slt-Slt (388)	to button,	Blk-Grn-Grn (055)		to coil	A7J5-9	button	A-17875
	Top Right Flipper	directly	Orn-Slt-Slt (388)	to button,	Blk-Yel-Yel (044)		to coil	A7J5-10	button	A-17875
	Bottom Right Flipper	directly	Orn-Slt-Slt (388)	to button,	Blk-Yel-Yel (044)		to coil	A7J5-10	button	A-17875

UPT = Under Playfield Transistor

www.inkochnito.nl