


**E-122-123  
TRANSFORMER  
WIRING FOR  
220/240 V.  
50/60 CYCLE INPUT.**




FOR 240 V. OR 240 V.  
INPUT TIE LUG 3 AND  
LUG 5 TOGETHER. PUT  
70-1 (ORANGE) WIRE  
ON LUG 1.

LUG 5 (115 V. TAP)

FOR 240 V. ONE SIDE OF  
LINE CORD ON LUG 7.

FOR 220 V. ONE SIDE OF  
LINE CORD ON LUG 9.

**E-122-124  
TRANSFORMER  
WIRING FOR  
115 V.  
60 CYCLE INPUT.**



FOR 115 V. INPUT  
PUT 70-1P (ORANGE)  
WIRE ON LUG 1.

ONE SIDE OF LINE CORD  
ON LUG 3.

**IMPORTANT**  
THESE SPECIALLY TAPPED  
TRANSFORMERS PROVIDE FOR  
LOCATIONS WITH LOW LINE  
VOLTAGE. MOVING THE 15  
(RED-WHITE) WIRE FROM THE  
LOW TAP (LUG 4) TO THE HIGH  
TAP (LUG 2) WILL ALLOW GAME  
TO OPERATE AT A LOW LINE  
VOLTAGE.

**CAUTION:**

AT NO TIME SHOULD THE 15  
(RED-WHITE) WIRE BE LEFT ON  
THE HIGH TAP WHEN LOCATION  
VOLTAGE EQUALS OR EXCEEDS  
110/220 VOLTS.