

Gottlieb's The Amazing Spiderman

Switch Matrix

	RETURN 0 A1J6-10 Blu-Blk-Blk (600)	RETURN 1 A1J6-11 Blu-Brn-Brn (611)	RETURN 2 A1J6-12 Blu-Red-Red (622)	RETURN 3 A1J6-13 Blu-Orn-Orn (633)	RETURN 4 A1J6-14 Blu-Yel-Yel (644)	RETURN 5 A1J6-15 Blu-Grn-Grn (655)	RETURN 6 A1J5-8 / A1J6-16 Blu-Blu-Blu (666)	RETURN 7 A1J5-1 / A1J6-17 Blu-Pur-Pur (677)
STROBE 0 A1J5-2 / A1J6-1 Yel-Blk-Blk (400)	#1 Right Drop Target Yel-Slt-Slt (488) SW.00	#1 Left Drop Target Red-Yel-Yel (244) SW.01	#1 Hole Brn-Orn-Orn (133) SW.02	Not Used SW.03	Not Used SW.04	Not Used SW.05	Not Used SW.06	Test Button Grn-Blk-Blk (500) SW.07
STROBE 1 A1J5-3 / A1J6-2 Yel-Brn-Brn (411)	#2 Right Drop Target Blu-Orn-Orn (633) SW.10	#2 Left Drop Target Red-Pur-Pur (277) SW.11	#2 Hole Brn-Grn-Grn (155) SW.12	Not Used SW.13	Not Used SW.14	Not Used SW.15	Not Used SW.16	Left Coin Chute Grn-Brn-Brn (511) SW.17
STROBE 2 A1J5-4 / A1J6-3 Yel-Red-Red (422)	#3 Right Drop Target Blu-Yel-Yel (644) SW.20	#3 Left Drop Target Red-Slt-Slt (288) SW.21	#3 Hole Brn-Pur-Pur (177) SW.22	Not Used SW.23	Not Used SW.24	Not Used SW.25	Not Used SW.26	Right Coin Chute Grn-Red-Red (522) SW.27
STROBE 3 A1J5-5 / A1J6-4 Yel-Orn-Orn (433)	#4 Right Drop Target Blu-Grn-Grn (655) SW.30	"A" Rollovers Blk-Grn-Grn (055) SW.31	10 Point Contacts (4) Blk-Red-Red (022) SW.32	Not Used SW.33	Not Used SW.34	Not Used SW.35	Not Used SW.36	Center Coin Chute Grn-Orn-Orn (533) SW.37
STROBE 4 A1J5-6 / A1J6-5 Yel-Yel-Yel (444)	#5 Right Drop Target Blu-Blu-Blu (666) SW.40	"B" Rollovers Blk-Yel-Yel (044) SW.41	50 Point Contacts (8) Blk-Orn-Orn (033) SW.42	Not Used SW.43	Not Used SW.44	Not Used SW.45	Not Used SW.46	Replay Button Grn-Yel-Yel (544) SW.47
STROBE 5 A1J5-7 / A1J6-6 Yel-Grn-Grn (455)	Rollover Button Brn-Yel-Yel (144) SW.50	Right Return & Left Outside Rollover Blk-Blk-Blk (000) SW.51	Not Used SW.52	Not Used SW.53	Not Used SW.54	Not Used SW.55	Not Used SW.56	Tilt Grn-Grn-Grn (555) Orn-Grn-Grn (355) SW.57
STROBE 6 A1J6-7 Yel-Blu-Blu (466)	Spin Target Slt-Blu-Blu (866) SW.60	Left Return & Right Outside Rollover Blk-Brn-Brn (011) SW.61	Not Used SW.62	Not Used SW.63	Not Used SW.64	Not Used SW.65	Not Used SW.66	Outhole Slt-Yel-Yel (844) SW.67
STROBE 7 A1J5-9 / A1J6-8 Yel-Pur-Pur (477)	Top Target Brn-Blu-Blu (166) SW.70	Side Target Blk-Blu-Blu (066) SW.71	Pop Bumpers (2) Slt-Slt-Slt (888) SW.72	Not Used SW.73	Not Used SW.74	Not Used SW.75	Not Used SW.76	Not Used SW.77

www.inkochnito.nl

Gottlieb's The Amazing Spiderman

Driverboard

transistor	connector	code	description	wire code	wire color	transistor type
Q01	A3J3-A	L0	Game Over Relay (Q)	288	Red-Slt-Slt	MPS-U45
Q Relay			Match	011	Blk-Brn-Brn	Q relay n.c.
Q Relay			Ball in Play	033	Blk-Orn-Orn	Q relay n.o.
Q02	A3J3-B	L1	Tilt Relay (T)	277	Red-Pur-Pur	MPS-U45
T Relay			Tilt	022	Brn-Red-Red	T relay n.o.
Q03	A3J5-2	L2	Coin Lockout	877	Slt-Pur-Pur	MPS-U45
Q04	A3J2-1 / A3J3-C	L3	Same Player Shoot Again	588	Grn-Slt-Slt	MPS-U45
Q05	A3J2-2	L4	Player 1	500	Grn-Blk-Blk	MPS-A13
Q06	A3J2-3	L5	Player 2	511	Grn-Brn-Brn	MPS-A13
Q07	A3J2-5	L6	Player 3	522	Grn-Red-Red	MPS-A13
Q08	A3J2-4	L7	Player 4	533	Grn-Orn-Orn	MPS-A13
Q09	A3J2-10	L8	Not Used	544	Grn-Yel-Yel	MPS-A13
Q10	A3J2-9	L9	Not Used	555	Grn-Grn-Grn	MPS-A13
Q11	A3J2-7	L10	High Game To Date	577	Grn-Pur-Pur	MPS-A13
Q12	A3J2-8	L11	Game Over	566	Grn-Blu-Blu	MPS-A13
Q13	A3J3-25	L12	Hole #1	100	Brn-Blk-Blk	MPS-U45
Q14	A3J3-24	L13	Hole #2	111	Brn-Brn-Brn	MPS-U45
Q15	A3J3-22	L14	Hole #3	122	Brn-Red-Red	MPS-U45
Q16	A3J3-23	L15	Right Drop Target #1	133	Brn-Orn-Orn	MPS-U45
Q17	A3J3-13	L16	Right Drop Target #2	144	Brn-Yel-Yel	MPS-U45
Q18	A3J3-14	L17	Right Drop Target #3	155	Brn-Grn-Grn	MPS-U45
Q19	A3J3-16	L18	Right Drop Target #4	166	Brn-Blu-Blu	MPS-U45
Q20	A3J3-15	L19	Right Drop Target #5	177	Brn-Pur-Pur	MPS-U45
Q21	A3J3-21	L20	Top Drop Target #1 (Multi-Bonus)	300	Orn-Blk-Blk	MPS-U45
Q22	A3J3-20	L21	Top Drop Target #2 (Adv. Multiplier)	311	Orn-Brn-Brn	MPS-U45
Q23	A3J3-18	L22	Top Drop Target #3 (Special)	322	Orn-Red-Red	MPS-U45
Q24	A3J3-19	L23	Special	333	Orn-Orn-Orn	MPS-U45
Q25	A3J3-9	L24	Advance Multiplier	344	Orn-Yel-Yel	MPS-U45
Q26	A3J3-10	L25	Multi-Bonus (3)	355	Orn-Grn-Grn	MPS-U45
Q27	A3J3-12	L26	Extra Ball Right	366	Orn-Blu-Blu	MPS-U45
Q28	A3J3-11	L27	Extra Ball Left	377	Orn-Pur-Pur	MPS-U45
Q29	A3J3-Y	L28	Spin Target	500	Grn-Blk-Blk	MPS-U45
Q30	A3J3-X	L29	Multiplier 2X	511	Grn-Brn-Brn	MPS-U45
Q31	A3J3-V	L30	Multiplier 3X	522	Grn-Red-Red	MPS-U45
Q32	A3J3-W	L31	Multiplier 4X	533	Grn-Orn-Orn	MPS-U45
Q33	A3J3-5	L32	Multiplier 5X	544	Grn-Yel-Yel	MPS-A13
Q34	A3J3-6	L33	Bonus 1000	555	Grn-Grn-Grn	MPS-A13
Q35	A3J3-K	L34	Bonus 2000	566	Grn-Blu-Blu	MPS-A13
Q36	A3J3-7	L35	Bonus 3000	577	Grn-Pur-Pur	MPS-A13
Q37	A3J4-1	L36	Bonus 4000	700	Pur-Blk-Blk	MPS-A13
Q38	A3J4-2	L37	Bonus 5000	711	Pur-Brn-Brn	MPS-A13
Q39	A3J4-4	L38	Bonus 6000	722	Pur-Red-Red	MPS-A13
Q40	A3J4-3	L39	Bonus 7000	733	Pur-Orn-Orn	MPS-A13
Q41	A3J3-4	L40	Bonus 8000	744	Grn-Yel-Yel	MPS-A13
Q42	A3J3-3	L41	Bonus 9000	755	Grn-Grn-Grn	MPS-A13
Q43	A3J3-T	L42	Bonus 10,000	766	Grn-Blu-Blu	MPS-A13
Q44	A3J3-2	L43	Bonus 20,000	777	Grn-Pur-Pur	MPS-A13
Q45	A3J3-D	L44	Score Bonus	800	Slt-Blk-Blk	MPS-U45
Q46	A3J3-F	L45	Right Return & Left Outlane	811	Slt-Brn-Brn	MPS-U45
Q47	A3J3-P	L46	Left Return & Right Outlane	822	Slt-Red-Red	MPS-U45
Q48	A3J3-M	L47	Pop Bumpers (2)	833	Slt-Orn-Orn	MPS-U45
Q49	A3J3-E	L48	Not Used	844	Slt-Yel-Yel	MPS-U45
Q50	A3J3-H	L49	"A" Rollovers (2)	855	Slt-Grn-Grn	MPS-U45
Q51	A3J3-R	L50	"B" Rollovers (2)	866	Slt-Blu-Blu	MPS-U45
Q52	A3J3-N	L51	Rollover Button	877	Slt-Pur-Pur	MPS-U45
Q53	A3J5-8	Solenoid 8	Knocker	888	Slt-Slt-Slt	2N6043
Q54	A3J6-3	Solenoid 3	Coin Counter 1	655	Blu-Grn-Grn	MPS-U45
Q55	A3J6-2	Solenoid 4	Coin Counter 2	644	Blu-Yel-Yel	MPS-U45
Q56	A3J6-1	Solenoid 7	Coin Counter 3	633	Blu-Orn-Orn	MPS-U45
Q57-Q58	A3J4-13	Solenoid 2	Hole Kickers #1 & #3	200	Red-Blk-Blk	MPS-U45 - 2N3055
Q59	A3J4-8	Solenoid 9	Outhole	244	Red-Yel-Yel	2N6043
Q60	A3J4-7	Solenoid 1	Hole Kicker #2	266	Red-Blu-Blu	2N6043
Q61-Q62	A3J4-6	Solenoid 5	Left Drop Target Bank Reset	211	Red-Brn-Brn	MPS-U45 - 2N3055
Q63-Q64	A3J4-12	Solenoid 6	Right Drop Target Bank Reset	233	Red-Orn-Orn	MPS-U45 - 2N3055

www.inkochnito.nl

Gottlieb's The Amazing Spiderman

Fuse List

designation	Wire in	Value	Wire out	description	location
F1	Blk-Slt-Slt (088)	12 Amp	Blk-Pur-Pur (077)	6.3VAC Lightbox Illumination	Bottom Board
F2		7½ Amp	Blk-Blu-Blu (066)	6.3VAC Playboard Illumination	Bottom Board
F3	Orn-Blk-Blk (300)	5 Amp Slo-Blo	Orn-Brn-Brn (311)	8VAC Controlled Lamps	Bottom Board
F4	Orn-Red-Red (322)	¼ Amp Slo-Blo	Orn-Orn-Orn (333)	12VAC Sound Board	Bottom Board
F5	Red-Brn-Brn (211)	5 Amp Slo-Blo	Red-Orn-Orn (233)	10VAC Power Supply	Bottom Board
F6	Red-Blu-Blu (266)	5 Amp Slo-Blo	Red-Pur-Pur (277)	25VAC Solenoids	Bottom Board
F7	Brn-Slt-Slt (188)	¼ Amp Slo-Blo	Brn-Blk-Blk (100)	60VAC Score Displays	Bottom Board
F8	--	5 Amp Slo-Blo	Grn-Slt-Slt (588)	115VAC Primary Fuse	Bottom Board
		2½ Amp Slo-Blo		230VAC Primary Fuse	Bottom Board
F9	Red-Red-Red (222)	1 Amp Slo-Blo	Yel-Pur-Pur (477)	Outhole	Playfield
				Hole Kicker #2	
				Hole Kicker #1	
				Hole Kicker #3	
				Left Drop Target Bank Reset	
F10	Red-Red-Red (222)	2 Amp Slo-Blo	Brn-Slt-Slt (188)	Right Drop Target Bank Reset	Playfield
F11	Orn-Slt-Slt (388)	2 Amp Slo-Blo	Yel-Blu-Blu (466)	Left Pop Bumper	Playfield
F12		2 Amp Slo-Blo	Brn-Brn-Brn (111)	Right Pop Bumper	Playfield

www.inkochnito.nl

Solenoids

	Solenoid description	Solenoid Type	Power Wire	Fuse	Transfer Wire	Coil Wire Color	Connector	Driver Tr.	Transistor Type	Coil Type
L0	Game Over Relay	controlled	Red-Red-Red (222)			Red-Slt-Slt (288)	A3J3-A	Q1	MPS-U45	A-16890
L1	Tilt Relay	controlled	Red-Red-Red (222)			Red-Pur-Pur (277)	A3J3-B	Q2	MPS-U45	A-16890
L2	Lockout	controlled	Red-Red-Red (222)			Slt-Pur-Pur (877)	A3J5-2	Q3	MPS-U45	A-16890
Sol. 1	Hole Kicker #2	controlled	Red-Red-Red (222)	F9	Yel-Pur-Pur (477)	Red-Blu-Blu (266)	A3J4-7	Q60	2N6043	A-16570
Sol. 2	Hole Kickers #1 and #3	controlled	Red-Red-Red (222)	F9	Yel-Pur-Pur (477)	Red-Blk-Blk (200)	A3J4-13	Q57 + Q58	MPS-U45 + 2N3055	A-16570
Sol. 3	Coin Counter #1	controlled	Red-Red-Red (222)			Blu-Grn-Grn (655)	A3J6-3	Q54	MPS-U45	
Sol. 4	Coin Counter #2	controlled	Red-Red-Red (222)			Blu-Yel-Yel (644)	A3J6-2	Q55	MPS-U45	
Sol. 5	Left Drop Target Bank Reset	controlled	Red-Red-Red (222)	F9	Yel-Pur-Pur (477)	Red-Brn-Brn (211)	A3J4-6	Q61 + Q62	MPS-U45 + 2N3055	A-18102
Sol. 6	Right Drop Target Bank Reset	controlled	Red-Red-Red (222)	F10	Brn-Slt-Slt (188)	Red-Orn-Orn (233)	A3J4-12	Q63 + Q64	MPS-U45 + 2N3055	A-17891
Sol. 7	Coin Counter #3	controlled	Red-Red-Red (222)			Blu-Orn-Orn (633)	A3J6-1	Q56	MPS-U45	
Sol. 8	Knocker	controlled	Red-Red-Red (222)			Slt-Slt-Slt (888)	A3J5-8	Q53	2N6043	A-5195
Sol. 9	Outhole	controlled	Red-Red-Red (222)	F9	Yel-Pur-Pur (477)	Red-Yel-Yel (244)	A3J4-8	Q59	2N6043	A-16570
	Left Pop Bumper	Pop Bumper Board	Orn-Slt-Slt (388)	F11	Yel-Blu-Blu (466)	Brn-Slt-Slt (188)	1A8J1-1	board 1 - Q1	2N6057	A-1496
	Right Pop Bumper	Pop Bumper Board	Orn-Slt-Slt (388)	F12	Brn-Brn-Brn (111)	Yel-Slt-Slt (488)	2A8J1-1	board 2 - Q1	2N6057	A-1496
	Left Kicking Rubber	directly	Orn-Slt-Slt (388)					switch		A-1496
	Right Kicking Rubber	directly	Orn-Slt-Slt (388)					switch		A-1496
	Top Left Flipper	directly	Orn-Slt-Slt (388)	to button,	Blk-Grn-Grn (055)	to coil	A7J5-9	button		A-17875
	Bottom Left Flipper	directly	Orn-Slt-Slt (388)	to button,	Blk-Grn-Grn (055)	to coil	A7J5-9	button		A-17875
	Top Right Flipper	directly	Orn-Slt-Slt (388)	to button,	Blk-Yel-Yel (044)	to coil	A7J5-10	button		A-17875
	Bottom Right Flipper	directly	Orn-Slt-Slt (388)	to button,	Blk-Yel-Yel (044)	to coil	A7J5-10	button		A-17875

www.inkochnito.nl