

Gottlieb's Star Race

Switch Matrix

	RETURN 0 A1J6-10 Blu-Blk-Blk (600)	RETURN 1 A1J6-11 Blu-Brn-Brn (611)	RETURN 2 A1J6-12 Blu-Red-Red (622)	RETURN 3 A1J6-13 Blu-Orn-Orn (633)	RETURN 4 A1J6-14 Blu-Yel-Yel (644)	RETURN 5 A1J6-15 Blu-Grn-Grn (655)	RETURN 6 A1J5-8 / A1J6-16 Blu-Blu-Blu (666)	RETURN 7 A1J5-1 / A1J6-17 Blu-Pur-Pur (677)
STROBE 0 A1J5-2 / A1J6-1 Yel-Blk-Blk (400)	#1 Rollover Button Orn-Slt-Slt (388) SW.00	Left Vari-Target "R" SW.01	#1 Top Drop Target Orn-Yel-Yel (344) SW.02	Left Return Rollover Blk-Brn-Brn (011) SW.03	10 Points (5) Red-Yel-Yel (244) SW.04	Not Used SW.05	Not Used SW.06	Test Button Grn-Blk-Blk (500) SW.07
STROBE 1 A1J5-3 / A1J6-2 Yel-Brn-Brn (411)	#2 Rollover Button Red-Blu-Blu (266) SW.10	Left Vari-Target "A" SW.11	#2 Top Drop Target Orn-Blu-Blu (366) SW.12	Left Return Rollover Blk-Red-Red (022) SW.13	10 points (2) Blk-Blk-Blk (000) SW.14	Not Used SW.15	Not Used SW.16	Left Coin Chute Grn-Brn-Brn (511) SW.17
STROBE 2 A1J5-4 / A1J6-3 Yel-Red-Red (422)	#1 Top Rollover Orn-Blk-Blk (300) SW.20	Left Vari-Target "T" SW.21	#3 Top Drop Target Orn-Pur-Pur (377) SW.22	Right Return Rollover Red-Blk-Blk (200) SW.23	Not Used SW.24	Not Used SW.25	Not Used SW.26	Center Coin Chute Grn-Red-Red (522) SW.27
STROBE 3 A1J5-5 / A1J6-4 Yel-Orn-Orn (433)	#2 Top Rollover Orn-Brn-Brn (311) SW.30	Left Vari-Target "S" SW.31	#1 Center Drop Target Slt-Yel-Yel (844) SW.32	Right Outside Rollover Red-Brn-Brn (211) SW.33	Not Used SW.34	Not Used SW.35	Not Used SW.36	Right Coin Chute Grn-Orn-Orn (533) SW.37
STROBE 4 A1J5-6 / A1J6-5 Yel-Yel-Yel (444)	#3 Top Rollover Orn-Red-Red (322) SW.40	Right Vari-Target "E" SW.41	#2 Center Drop Target Slt-Grn-Grn (855) SW.42	Right Target Yel-Slt-Slt (488) SW.43	Not Used SW.44	Not Used SW.45	Not Used SW.46	Replay Button Grn-Yel-Yel (544) SW.47
STROBE 5 A1J5-7 / A1J6-6 Yel-Grn-Grn (455)	#4 Top Rollover Orn-Orn-Orn (333) SW.50	Right Vari-Target "C" SW.51	#3 Center Drop Target Slt-Blu-Blu (866) SW.52	#3-4-5 Rollover Button Blk-Grn-Grn (055) SW.53	Not Used SW.54	Not Used SW.55	Not Used SW.56	Tilt Grn-Grn-Grn (555) Brn-Slt-Slt (188) SW.57
STROBE 6 A1J6-7 Yel-Blu-Blu (466)	Left Side Rollover Blk-Yel-Yel (044) SW.60	Right Vari-Target "A" SW.61	#4 Center Drop Target Slt-Pur-Pur (877) SW.62	Not Used SW.63	Not Used SW.64	Not Used SW.65	Not Used SW.66	Outhole Slt-Slt-Slt (888) SW.67
STROBE 7 A1J5-9 / A1J6-8 Yel-Pur-Pur (477)	Left Outside Rollover Blk-Orn-Orn (033) SW.70	Right Vari-Target "R" SW.71	Hole Kicker Blk-Pur-Pur (077) SW.72	Pop Bumpers (2) Blk-Blu-Blu (066) SW.73	Not Used SW.74	Not Used SW.75	Not Used SW.76	Not Used SW.77

www.inkochnito.nl

Gottlieb's Star Race

Driverboard

transistor	connector	code	description	wire code	wire color	transistor type
Q01	A3J3-A	L0	Game Over Relay (Q)	288	Red-Slt-Slt	MPS-U45
Q Relay			Match	011	Blk-Brn-Brn	Q relay n.c.
Q Relay			Ball in Play	033	Blk-Orn-Orn	Q relay n.o.
Q02	A3J3-B	L1	Tilt Relay (T)	277	Red-Pur-Pur	MPS-U45
T Relay			Tilt	022	Brn-Red-Red	T relay n.o.
Q03	A3J5-2	L2	Coin Lockout	877	Slt-Pur-Pur	MPS-U45
Q04	A3J2-1 / A3J3-C	L3	Same Player Shoot Again	588	Grn-Slt-Slt	MPS-U45
Q05	A3J2-2	L4	Player 1	500	Grn-Blk-Blk	MPS-A13
Q06	A3J2-3	L5	Player 2	511	Grn-Brn-Brn	MPS-A13
Q07	A3J2-5	L6	Player 3	522	Grn-Red-Red	MPS-A13
Q08	A3J2-4	L7	Player 4	533	Grn-Orn-Orn	MPS-A13
Q09	A3J2-10	L8	Not Used	544	Grn-Yel-Yel	MPS-A13
Q10	A3J2-9	L9	Not Used	555	Grn-Grn-Grn	MPS-A13
Q11	A3J2-7	L10	High Game To Date	577	Grn-Pur-Pur	MPS-A13
Q12	A3J2-8	L11	Game Over	566	Grn-Blu-Blu	MPS-A13
Q13	A3J3-25	L12	Left Vari-Target "S"	100	Brn-Blk-Blk	MPS-U45
Q14	A3J3-24	L13	Left Vari-Target "T"	111	Brn-Brn-Brn	MPS-U45
Q15	A3J3-22	L14	Left Vari-Target "A"	122	Brn-Red-Red	MPS-U45
Q16	A3J3-23	L15	Left Vari-Target "R"	133	Brn-Orn-Orn	MPS-U45
Q17	A3J3-13	L16	Right Vari-Target "R"	144	Brn-Yel-Yel	MPS-U45
Q18	A3J3-14	L17	Right Vari-Target "A"	155	Brn-Grn-Grn	MPS-U45
Q19	A3J3-16	L18	Right Vari-Target "C"	166	Brn-Blu-Blu	MPS-U45
Q20	A3J3-15	L19	Right Vari-Target "E"	177	Brn-Pur-Pur	MPS-U45
Q21	A3J3-21	L20	Top Drop Targets 5000	300	Orn-Blk-Blk	MPS-U45
Q22	A3J3-20	L21	Top Drop Targets 10,000 & Left Side R.O.	311	Orn-Brn-Brn	MPS-U45
Q23	A3J3-18	L22	Top Drop Targets 15,000 & Right Target	322	Orn-Red-Red	MPS-U45
Q24	A3J3-19	L23	Top Drop Targets Extra Ball	333	Orn-Orn-Orn	MPS-U45
Q25	A3J3-9	L24	Not Used	344	Orn-Yel-Yel	MPS-U45
Q26	A3J3-10	L25	20,000 Bonus & Scores Bonus	355	Orn-Grn-Grn	MPS-U45
Q27	A3J3-12	L26	Bonus 1000	366	Orn-Blu-Blu	MPS-U45
Q28	A3J3-11	L27	Bonus 2000	377	Orn-Pur-Pur	MPS-U45
Q29	A3J3-Y	L28	Bonus 3000	500	Grn-Blk-Blk	MPS-U45
Q30	A3J3-X	L29	Bonus 4000	511	Grn-Brn-Brn	MPS-U45
Q31	A3J3-V	L30	Bonus 5000	522	Grn-Red-Red	MPS-U45
Q32	A3J3-W	L31	Bonus 6000	533	Grn-Orn-Orn	MPS-U45
Q33	A3J3-5	L32	Bonus 7000	544	Grn-Yel-Yel	MPS-A13
Q34	A3J3-6	L33	Bonus 8000	555	Grn-Grn-Grn	MPS-A13
Q35	A3J3-K	L34	Bonus 9000	566	Grn-Blu-Blu	MPS-A13
Q36	A3J3-7	L35	Bonus 10,000	577	Grn-Pur-Pur	MPS-A13
Q37	A3J4-1	L36	Yellow Multiplier 2X	700	Pur-Blk-Blk	MPS-A13
Q38	A3J4-2	L37	Yellow Multiplier 3X	711	Pur-Brn-Brn	MPS-A13
Q39	A3J4-4	L38	Yellow Multiplier 4X	722	Pur-Red-Red	MPS-A13
Q40	A3J4-3	L39	Yellow Multiplier 5X	733	Pur-Orn-Orn	MPS-A13
Q41	A3J3-4	L40	Green Multiplier 2X	744	Grn-Yel-Yel	MPS-A13
Q42	A3J3-3	L41	Green Multiplier 3X	755	Grn-Grn-Grn	MPS-A13
Q43	A3J3-T	L42	Green Multiplier 4X	766	Grn-Blu-Blu	MPS-A13
Q44	A3J3-2	L43	Green Multiplier 5X	777	Grn-Pur-Pur	MPS-A13
Q45	A3J3-D	L44	Yellow Adv. Mult. & Left Outside R.O. (2)	800	Slt-Blk-Blk	MPS-U45
Q46	A3J3-F	L45	Yellow Adv. Mult. & Left Return R.O. (2)	811	Slt-Brn-Brn	MPS-U45
Q47	A3J3-P	L46	Green Adv. Multi. & Right Return R.O. (2)	822	Slt-Red-Red	MPS-U45
Q48	A3J3-M	L47	Green Adv. Multi. & Right Outside R.O. (2)	833	Slt-Orn-Orn	MPS-U45
Q49	A3J3-E	L48	Top Rollover #1	844	Slt-Yel-Yel	MPS-U45
Q50	A3J3-H	L49	Top Rollover #2	855	Slt-Grn-Grn	MPS-U45
Q51	A3J3-R	L50	Top Rollover #3	866	Slt-Blu-Blu	MPS-U45
Q52	A3J3-N	L51	Top Rollover #4	877	Slt-Pur-Pur	MPS-U45
Q53	A3J5-8	Solenoid 8	Knocker	888	Slt-Slt-Slt	2N6043
Q54	A3J6-3	Solenoid 3	Coin Counter 1	655	Blu-Grn-Grn	MPS-U45
Q55	A3J6-2	Solenoid 4	Coin Counter 2	644	Blu-Yel-Yel	MPS-U45
Q56	A3J6-1	Solenoid 7	Coin Counter 3	633	Blu-Orn-Orn	MPS-U45
Q57-Q58	A3J4-13	Solenoid 2	Hole Kicker	200	Red-Blk-Blk	MPS-U45 - 2N3055
Q59	A3J4-8	Solenoid 9	Outhole	244	Red-Yel-Yel	2N6043
Q60	A3J4-7	Solenoid 1	Left & Right Vari-Target Reset	266	Red-Blu-Blu	2N6043
Q61-Q62	A3J4-6	Solenoid 5	Top Drop Target Bank Reset	211	Red-Brn-Brn	MPS-U45 - 2N3055
Q63-Q64	A3J4-12	Solenoid 6	Center Drop Target Bank Reset	233	Red-Orn-Orn	MPS-U45 - 2N3055

Gottlieb's Star Race

Fuse List

designation	Wire in	Value	Wire out	description	location
F1	Blk-Slt-Slt (088)	10 Amp	Blk-Pur-Pur (077)	6.3VAC Lightbox Illumination	Bottom Board
F2		12 Amp	Blk-Blu-Blu (066)	6.3VAC Playboard Illumination	Bottom Board
F3	Orn-Blk-Blk (300)	7½ Amp Slo-Blo	Orn-Brn-Brn (311)	8VAC Controlled Lamps	Bottom Board
F4	Orn-Red-Red (322)	¼ Amp Slo-Blo	Orn-Orn-Orn (333)	12VAC Sound Board	Bottom Board
F5	Red-Brn-Brn (211)	5 Amp Slo-Blo	Red-Orn-Orn (233)	10VAC Power Supply	Bottom Board
F6	Red-Blu-Blu (266)	8 Amp Slo-Blo	Red-Pur-Pur (277)	25VAC Solenoids	Bottom Board
F7	Brn-Slt-Slt (188)	¼ Amp Slo-Blo	Brn-Blk-Blk (100)	60VAC Score Displays	Bottom Board
F8	--	5 Amp Slo-Blo	Grn-Slt-Slt (588)	115VAC Primary Fuse	Bottom Board
		2½ Amp Slo-Blo		230VAC Primary Fuse	Bottom Board
F9	Red-Red-Red (222)	1 Amp Slo-Blo	Red-Pur-Pur (277)	Outhole	Playfield
				Hole Kicker	
				Top Drop Target Bank Reset	
F10	Red-Red-Red (222)	2 Amp Slo-Blo	Red-Slt-Slt (288)	Center Drop Target Bank Reset	Playfield
F11	Orn-Slt-Slt (388)	2 Amp Slo-Blo	Red-Orn-Orn (233)	Left Pop Bumper	Playfield
F12		2 Amp Slo-Blo	Red-Grn-Grn (255)	Right Pop Bumper	Playfield

www.inkochnito.nl

Solenoids

	Solenoid description	Solenoid Type	Power Wire	Fuse	Transfer Wire	Coil Wire Color	Connector	Driver Tr.	Transistor Type	Coil Type
L0	Game Over Relay	controlled	Red-Red-Red (222)			Red-Slt-Slt (288)	A3J3-A	Q1	MPS-U45	A-16890
L1	Tilt Relay	controlled	Red-Red-Red (222)			Red-Pur-Pur (277)	A3J3-B	Q2	MPS-U45	A-16890
L2	Lockout	controlled	Red-Red-Red (222)			Slt-Pur-Pur (877)	A3J5-2	Q3	MPS-U45	A-16890
Sol. 1	Left & Right Vari-Target Reset	controlled	Red-Red-Red (222)			Red-Blu-Blu (266)	A3J4-7	Q60	2N6043	A-17564 (2)
Sol. 2	Hole Kicker	controlled	Red-Red-Red (222)	F9	Red-Pur-Pur (277)	Red-Blk-Blk (200)	A3J4-13	Q57 + Q58	MPS-U45 + 2N3055	A-16570
Sol. 3	Coin Counter #1	controlled	Red-Red-Red (222)			Blu-Grn-Grn (655)	A3J6-3	Q54	MPS-U45	
Sol. 4	Coin Counter #2	controlled	Red-Red-Red (222)			Blu-Yel-Yel (644)	A3J6-2	Q55	MPS-U45	
Sol. 5	Top Drop Target Bank Reset	controlled	Red-Red-Red (222)	F9	Red-Pur-Pur (277)	Red-Brn-Brn (211)	A3J4-6	Q61 + Q62	MPS-U45 + 2N3055	A-18102
Sol. 6	Center Drop Target Bank Reset	controlled	Red-Red-Red (222)	F10	Red-Slt-Slt (288)	Red-Orn-Orn (233)	A3J4-12	Q63 + Q64	MPS-U45 + 2N3055	A-18318
Sol. 7	Coin Counter #3	controlled	Red-Red-Red (222)			Blu-Orn-Orn (633)	A3J6-1	Q56	MPS-U45	
Sol. 8	Knocker	controlled	Red-Red-Red (222)			Slt-Slt-Slt (888)	A3J5-8	Q53	2N6043	A-5195
Sol. 9	Outhole	controlled	Red-Red-Red (222)	F9	Red-Pur-Pur (277)	Red-Yel-Yel (244)	A3J4-8	Q59	2N6043	A-16570
	Left Pop Bumper	Pop Bumper Board	Orn-Slt-Slt (388)	F11	Red-Orn-Orn (233)	Brn-Slt-Slt (188)	1A8J1-1	board 1 - Q1	2N6057	A-1496
	Right Pop Bumper	Pop Bumper Board	Orn-Slt-Slt (388)	F12	Yel-Pur-Pur (477)	Yel-Slt-Slt (488)	2A8J1-1	board 2 - Q1	2N6057	A-1496
	Left Kicking Rubber	directly	Orn-Slt-Slt (388)					switch		A-1496
	Right Kicking Rubber	directly	Orn-Slt-Slt (388)					switch		A-1496
	Lower Left Flipper	directly	Orn-Slt-Slt (388)	to button,	Blk-Grn-Grn (055)	to coil	A7J5-9	button		A-17875
	Upper Left Flipper	directly	Orn-Slt-Slt (388)	to button,	Blk-Grn-Grn (055)	to coil	A7J5-9	button		A-17875
	Lower Right Flipper	directly	Orn-Slt-Slt (388)	to button,	Blk-Yel-Yel (044)	to coil	A7J5-10	button		A-17875
	Upper Right Flipper	directly	Orn-Slt-Slt (388)	to button,	Blk-Yel-Yel (044)	to coil	A7J5-10	button		A-17875

www.inkochnito.nl