

STERN 16B-3 TRANSFORMER WIRING CONNECTION INSTRUCTIONS

115 / 120V., 50 / 60 Cycle Input.


Varistor - Soldered to Line Filter on Left Side of Cabinet.

Must be Stern Part No. 25A-18-1.

Solder Lugs 1 & 3
Together. Solder Heavy
Red Wire To Lug 1

120V
Solder Lugs 5 & 7
Together. Solder Heavy
Yellow Wire To Lug 5.

115V
Solder Lugs 9 & 11
Together. Solder Heavy
Yellow Wire To Lug 9



220 / 240V., 50 / 60 Cycle Input.

Varistor - Soldered to Line Filter on Left Side of Cabinet.


Must be Stern Part No. 25A-18-2.

Solder Heavy Red Wire
To Lug 1

Solder Lugs 3 & 5
Together

240V
Solder Heavy Yellow
Wire To Lug 7

220V
Solder Heavy Yellow
Wire To Lug 12



12A-153

Font used: Helvetica, AlternateGothic2 BT, CentSchbook Mono BT
Size: 203 x 114 mm
12A-153 transformer card confirmed.

Enjoy and have fun,
Peter

www.inkochnito.nl

If you like my work, please send me a donation via PayPal.