

Fuse List

Rectifier Board TA-100		
F1	6.5V Switched illumination	10A, 250V
F2	230V Display power input	0.75A, 250V
F3	5V Unregulated input	4A, 250V
F4	43V Solenoids (3 flippers)	5A, 250V
F5	6.5V General illumination	20A, 250V
F6	Main fuse	3A, 250V, SB
Sol. Dr./Volt. Reg. SDU-100		
F1	190V Display power output (if present)	0.25A, 250V
Under the Playfield fuses		
F1	Playfield Solenoids	1A, 250V, SB

